arXiv:0801.1583v1 [cond-mat.stat-mech] 10 Jan 2008

Order parameter configurations in the Lifshitz-type incommensurate ferroelectric thin films

Sergey A. Ktitorov
A.F. Ioffe Physicotechnical Institute of the Russian Academy of Sciences,
Polytechnicheskaja str. 26, St. Petersburg 194021,
Russia; St. Petersburg Electrotechnical University,
prof. Popov str. 5, St. Petersburg 197376, Russia

Philip A. Pogorelov
St. Petersburg State University, Pervogo Maya str. 100, Petrodvoretz, St. Petersburg 198504, Russia

The Dzialoshinskii model of periodic and helicoidal structures has been analyzed without neglecting of the amplitude function oscillations. The amplitude function oscillations are shown to be important for understanding of the nature of the phase function. Analytic consideration is carried out in the limit of small anisotropy (neglecting the cosine term in the Hamiltonian). Surprisingly, the phase jumps survive even in the limit of the vanishing anisotropy.

I. INTRODUCTION

The theory of modulated structures in macroscopic ferromagnets [1], ferroelectrics [2] and metal alloys [3] has a rich history. The number of works dedicated to a study of the modulated structures in small samples is significantly less [4]. The standard approach to the theory of the modulated structures (including the incommensurate ones) uses the constant order parameter amplitude function approximation [2], [5]. Our consideration of the bounded sample (thin film, in particular) requires us to drop this approximation: the order parameter must satisfy some boundary conditions and it is unlikely to find a solution with constant order parameter satisfying these conditions. That is why we have to consider a generic case of connected set of the nonlinear equations for the order parameter amplitude and phase functions. We will show here that the solutions of this system are significantly more complicated, than in the constant order parameter approximation.

II. FREE ENERGY AND THE EQUATIONS FOR THE ORDER PARAMETER FOR A FERROELECTRIC WITH THE LIFSHITZ INVARIANTS

The Landau free energy functional reads [5]:

$$\begin{aligned}\Phi \;&= \int dz\left\{-r(\eta_1^2+\eta_2^2)+u_1(\eta_1^2+\eta_2^2)^2+u_2(\eta_1^2\eta_2^2)\right\}+\\ &+\int dz\left\{\sigma\left(\eta_2\frac{\partial\eta_1}{\partial z}-\eta_1\frac{\partial\eta_2}{\partial z}\right)+\gamma\left[\left(\frac{\partial\eta_1}{\partial z}\right)^2+\left(\frac{\partial\eta_2}{\partial z}\right)^2\right]\right\},\end{aligned} \tag{1}$$

where η_1 and η_2 are the order parameter components; we consider only one-dimensional configurations; parameters r, σ, u_1, u_2 and γ are the Landau free energy expansion coefficient. Introducing the amplitude and phase variables

$$\eta_1=\rho\cos\varphi, \eta_2=\rho\sin\varphi,$$

we obtain the following expression for the Landau free energy:

$$\begin{aligned}\Phi = \int dz\{-r\rho^2+u\rho^4+w\rho^n(1+\cos n\varphi)\\ -\sigma\rho^2\frac{\partial\varphi}{\partial z}+\gamma\left[\left(\frac{\partial\rho}{\partial z}\right)^2+\rho^2\left(\frac{\partial\varphi}{\partial z}\right)^2\right]\}.\end{aligned} \tag{2}$$

Varying the free energy we obtain the equilibrium equations [5]

$$\begin{aligned}-r\rho+2u\rho^3+\frac{n}{2}w\rho^{n-1}(1+\cos n\varphi)+\gamma\rho(\frac{\partial\varphi}{\partial z})^2-\\ \gamma\frac{\partial^2\rho}{\partial z^2}-\sigma\rho\frac{\partial\varphi}{\partial z}=0,\end{aligned} \tag{3}$$

$$\gamma\rho^2\frac{\partial^2\varphi}{\partial z^2}+2\gamma\rho\frac{\partial\rho}{\partial z}\frac{\partial\varphi}{\partial z}-\sigma\rho\frac{\partial\rho}{\partial z}+\frac{n}{2}w\rho^n\sin n\varphi=0. \tag{4}$$

Here n is an integer number describing the system symmetry. Now we introduce the dimensionless variables:

$$\rho=\sqrt{\frac{r}{2u}}R,\xi=z\sqrt{\frac{r}{\gamma}},\frac{dR}{dz}=\frac{dR}{d\xi}\sqrt{\frac{r}{\gamma}},$$
$$\frac{\sigma}{\sqrt{\gamma r}}=T,u^{1-\frac{n}{2}}nwr^{\frac{n}{2}-2}2^{-\frac{n}{2}}=K. \tag{5}$$

Then the equations (3) and (4) take the form

$$R''-R^3+(1-\varphi'^2+T\varphi')R-R^{n-1}K(\cos n\varphi+1)=0, \tag{6}$$

$$\varphi''+2\frac{R'}{R}\varphi'-\frac{R'}{R}T+R^{n-2}K\sin n\varphi=0. \tag{7}$$

III. APPROXIMATE ANALYTIC SOLUTION

Let us begin from the limit $K=0$. Then the equation (7) can be solved:

$$\varphi'\equiv\psi=\frac{C_0}{R^2}+\frac{T}{2}, \tag{8}$$

where $C_0=\left[\psi(0)-\frac{T}{2}\right]R(0)^2$ is the integration constant, which is determined by the initial conditions $\psi(0)$ and $R(0)$. Now we can substitute this expression for φ' into the equation (6). We obtain in result a closed equation for the amplitude function R :

$$R''-R^3+R(1+\frac{T^2}{4})-\frac{C_0^2}{R^3}=0. \tag{9}$$

This equation can be interpreted as a dynamics equation with the effective potential:

$$U=\frac{R^2}{2}(1+\frac{T^2}{4})-\frac{R^4}{4}+\frac{C_0^2}{2R^2}. \tag{10}$$

An interesting feature of this potential is its dependence on the initial conditions via the constant C_0^2. There exists a domain of parameters, where the potential has a minimum and, therefore, an oscillating solution for the amplitude function can take place. A condition of the maximum and minimum points merging into the inflection point with the horizontal derivative $U'(R)=U''(R)=0$ gives the equation

$$T^6+12T^4+48T^2+64-432C_0^2=0$$

However, a presence of a minimum is necessary but not sufficient condition: an oscillating solution will not exist if the initial point is situated outside the potential well.

A border line for the domain, where oscillating solutions can exist is depicted here:



FIG.1. A border line for the domain, where oscillating solutions can exist.

If we have a solution for the amplitude function $R(\xi)$, the phase function $\varphi(\xi)$ is given by the equation (8). The phase function consists from two terms: a slow contribution stemming from the second term in (8) and more or less diffused jumps due to the first term in this equation. It is important that the jump value equals exactly to π :

The first integral of 6 reads $\frac{dR}{d\xi} = \sqrt{2(E-U)}$, so $d\xi = \frac{dR}{\sqrt{2(E-U)}}$.

Notice that the jump value $\int \frac{C_0}{R^2} d\xi$ calculated in the vicinity of the $R(\xi)$ minimum equals to

$$\Delta\varphi \ = \int \frac{C_0}{R^2} d\xi = \int \frac{C_0}{R^2} \frac{dR}{\sqrt{2(E-U)}} \simeq 2 \int_{R_0}^{R_e} \frac{C_0 dR}{R^2 \sqrt{2(\frac{C_0^2}{2R_0^2} - \frac{C_0^2}{2R^2})}} =$$

$$= 2 \int_{R_0}^{R_e} \frac{dR}{R\sqrt{\frac{R^2}{R_0^2} - 1}} = 2 \arccos \left| \frac{R_0}{Re} \right| \simeq \pi, \qquad (11)$$

where $R_e \gg R_0$. We have used the first integral of (9) above. Only leading terms of $U(R)$ were taken into account. Note that the model (2), which can be reduced to the sine-Gordon model in the limit of $R = const$, admits solutions with jumps exactly equal to $\pm\pi$ (topological charge [6]). However, we have obtained a similar result within the approximation $K = 0$, i.e. neglecting the cosine term in (2)! As it is seen from the formulae 11, these phase jumps appear due to the excursion of the amplitude function near the singularity $\frac{C_0}{R^2}$.

The equation (9) can be solved analytically, but we will present below numerical solutions both for $K = 0$ and $K \neq 0$.

IV. NUMERICAL SOLUTION FOR K = 0

Some results of calculation of the amplitude and phase functions spatial dependence for the case of $K = 0$ are presented below. Figures 2 – 5 and 6 – 9 differ only by initial values of the amplitude function: in the case of figures 2 – 5 we have small initial amplitude function and, therefore, oscillations of the amplitude function are near to harmonic ones, while in the case of figures 6 – 9 the initial amplitude function is near to the apex of the hump and, therefore, we have a train of solitons.



FIG.2. Effective potential for $n = 4$, $K = 0$, $T = 1$, $R(0) = 0.3$, $R'(0) = 0$, $\varphi(0) = 0$, $\varphi'(0) = 0.3$.
Vertical dash marks $R(0)$ value.



FIG. 3. Spatial dependence of the amplitude function for $n = 4$, $K = 0$, $T = 1$, $R(0) = 0.3$, $R'(0) = 0$, $\varphi(0) = 0$, $\varphi'(0) = 0.3$



FIG. 4. Spatial dependence of the phase function for $n = 4$, $K = 0$, $T = 1$, $R(0) = 0.3$, $R'(0) = 0$, $\varphi(0) = 0$
(a) thin line $\varphi'(0) = 0.3$
(b) heavy line $\varphi'(0) = 0.7$.



FIG. 5. Amplitude-phase polar diagram for $n = 4$, $K = 0$, $T = 1$, $R(0) = 0.3$, $R'(0) = 0$, $\varphi(0) = 0$
(a) thin line $\varphi'(0) = 0.3$
(b) heavy line $\varphi'(0) = 0.7$.



FIG. 6. Effective potential for $n = 4$, $K = 0$, $T = 1$, $R(0) = 1.099$, $R'(0) = 0$, $\varphi(0) = 0$, $\varphi'(0) = 0.3$
Vertical dash marks $R(0)$ value.



FIG. 7. Spatial dependence of the amplitude function for $n = 4$, $K = 0$, $T = 1$, $R(0) = 1.099$, $R'(0) = 0$, $\varphi(0) = 0$, $\varphi'(0) = 0.3$



FIG. 8. Spatial dependence of the phase function for $n = 4$, $K = 0$, $T = 1$, $R(0) = 1.099$, $R'(0) = 0$, $\varphi(0) = 0$
(a) thin line $\varphi'(0) = 0.3$
(b) heavy line $\varphi'(0) = 0.7$.



FIG. 9. Amplitude-phase polar diagram for $n = 4$, $K = 0$, $T = 1$, $R(0) = 1.099$, $R'(0) = 0$, $\varphi(0) = 0$
(a) thin line $\varphi'(0) = 0.3$
(b) heavy line $\varphi'(0) = 0.7$.

V. NUMERICAL SOLUTION FOR K

Results of the numerical solution of our equations in the case of $K \neq 0$ are presented in the figures 10 – 15. The following important distinctions from the case of $K = 0$ must be mentioned:

(i) The periodicity of the spatial dependence is broken.

(ii) The frequency and amplitude modulation can be seen in Figs. 10 and 11.

(iii) A direction of the phase function staircase spatial dependence may change to the opposite after some number of steps. The number of steps between neighboring direction changes is random (see FIG. 15).

(iv) There exists a parameter range, where the trajectories in the polar diagram show closed periodic movement: a synchronization with the periodic contribution of the sine of the monotonously increasing component of the phase function takes place.



FIG. 10. Spatial dependence of the amplitude function for $n = 4$, $K = 1.6$, $T = 1$, $R(0) = 0.3$, $R'(0) = 0$, $\varphi(0) = 0$, $\varphi'(0) = 0.3$



FIG. 11. Spatial dependence of the amplitude function for $n = 4$, $K = 1.6$, $T = 1$, $R(0) = 0.3$, $R'(0) = 0$, $\varphi(0) = 0$, $\varphi'(0) = 0.75$: thin line

Spatial dependence of the parameter C^2 (see below) in arbitrary units: heavy line.



FIG. 12. Spatial dependence of the phase function for $n = 4$, $K = 1.6$, $T = 1$, $R(0) = 0.3$, $R'(0) = 0$, $\varphi(0) = 0$

(a) thin line $\varphi'(0) = 0.3$
(b) heavy line $\varphi'(0) = 0.75$.



FIG. 13. Amplitude-phase polar diagram for $n = 4$, $K = 1.6$, $T = 1$, $R(0) = 0.3$, $R'(0) = 0$, $\varphi(0) = 0, \varphi'(0) = 0.3$



FIG. 14. Amplitude-phase polar diagram for $n = 4$, $K = 1.6$, $T = 1$, $R(0) = 0.3$, $R'(0) = 0$, $\varphi(0) = 0, \varphi'(0) = 0.75$

VI. DISCUSSION

Thus, the main distinctions of the solution in the case of the non-vanishing anisotropy parameter K are a random change of the jumps direction (see FIG. 12) and an amplitude modulation of the amplitude function (see FIG. 11). Just these random direction changes lead to the tangled trajectory in polar coordinates presented in FIG 14.

In the case of $K = 0$ we introduced the integration constant C_0 (8). Let us introduce the function:

$$C(\xi) = \left[\psi(\xi) - \frac{T}{2}\right] R(\xi)^2.$$

Direct differentiation shows that this function reduces to a constant in the case of vanishing anisotropy parameter K:

$$\begin{aligned} \frac{dC}{d\xi} &= 2R\frac{dR}{d\xi}\left[\psi - \frac{T}{2}\right] + R^2\frac{d\psi}{d\xi} = \\ &= R^2(2\frac{R'}{R}\varphi' - T\frac{R'}{R} + \varphi'') = \\ &= R^2(-R^{n-2}K\sin n\varphi) = -R^nK\sin n\varphi. \end{aligned} \tag{12}$$



FIG. 15. Spatial dependence of the parameter C for $n = 4$, $K = 1.6$, $T = 1$, $R(0) = 0.3$, $R'(0) = 0$, $\varphi(0) = 0, \varphi'(0) = 0.75$
(a) thin line C'
(b) heavy line C.

Comparison of FIG. 15 and FIG. 12 confirms that changes of the direction take place in the points where $C(\xi)$ function changes its sign.

VII. CONCLUSION

We have shown in this paper that the constant amplitude approximation gives a poor description of the real picture of the spatial evolution of the amplitude and phase functions for the model of the incommensurate ferroelectric with the Lifshitz invariant.

---

[1] I. Dzyaloshinskii, Soviet Physics JETP 19, 960 (1964).
[2] A.P. Levaniuk and D.G. Sannikov, Fiz. Tverd. Tela 18, 423 (1976).
[3] A.G. Khachaturian, *Theory of Structural Transformations in Solids, Wiley, 1983*
[4] E.V. Charnaya, S.A. Ktitorov, O.S. Pogorelova, Ferroelectrics, 297, 29 (2003).
[5] Ju. A. Iziumov, V.N. Syromiatnikov, Phase Transitions and Crystal Symmetry, Moscow, Nauka, 1984.
[6] Mark J. Ablowitz and Harvey Segur, Solitons and the Inverse Scattering Transform, SIAM, Philadelphia, 1981